



門禁繼電器控制盒

RELAY BOX

Site Security, Access Control, Elevator Control 場所安全、門禁管制、樓層控制

Distributor Wanted / OEM, ODM Welcome
CE/FCC/RoHS Compliance ISO 9001:2008 Certified

Specifications | 規格

Function 功能	Model name 型號	BF-20	BF-50	BF-333
Multi-door or Single-door controller readers support 搭配多門控制器或感應讀頭控制單門		BF-630/BF-830 BF-660/BF-670 BF-880/BF-870 SEMAC, WebPass	BF-660/BF-670 BF-880/BF-870 SEMAC, WebPass	BF-660/BF-670 BF-880/BF-870 SEMAC-S3
Watch Dog built-in 內建看門狗		●	●	●
Working Voltage (DC) 額定電壓		9 ~ 24VDC / 1A		
Working Current (mA) 額定電流		200mA ~ 400mA		800mA ~ 1000mA
LED Control dry contact 讀頭LED控制接點			●	
Buzzer Control dry contact 讀頭蜂鳴器控制接點			●	
Card Reader Sensor dry contact 讀頭讀卡控制接點			●	
Reader detecting dry contact 讀頭偵測接點			●	
Wiegand IN communication dry contact WG in 通訊接點		1	2	
RS485 communication dry contact RS-485 通訊接點		●	●	●
Emergency mode dry contact 緊急模式接點		●	●	●
Emergency mode: Exit button's still available while disconnected with Terminal 緊急模式下與控制器斷訊，開門按鈕仍作用		●	●	Emergency Switch removing the control of all floors. 緊急輸入點，可解除所有樓層管制
Sensor dry contact 門磁接點		●	●	
Buzzer Enable/Disable option 蜂鳴器啟用/關閉功能			●	
Sensor circuit detecting 門磁線路檢測功能			●	
Exit Button dry contact 開門按鈕接點		●	●	
Door Open Relay 開門繼電器		1	1	16
Relay Spec. 繼電器規格		3A/125VAC/30VDC		3A/125VAC 2A 30VDC
Event/Log Relay 事件處理繼電器		2	2	
Door no. Configurations 設定門號		Main Door & Door no. 1~8 主門與 1~8 門	Door no. 1~8 1~8 門	Manages up to 8 elevator controllers, totally 128 multistories. 並聯 8 台控制 128 個樓層
Weight(g.) 重量		100	140	655
Dimension(mm) 尺寸		91 × 51 × 30	106 × 100 × 26.5	165 × 140 × 37

Application | 應用

BF-20/BF-50 Relay box is installed and hidden on ceiling T girds, so the door relay won't be released even the controller is destroyed.

BF-20/BF-50 繼電器置放於輕鋼架上，即使主機遭到破壞，在無損及繼電器的狀況下，仍無法開門。



Welcome to **CHIYU**

Chiayi: 886-5-2325465 • Taipei: 886-2-25491289 • Kaohsiung: 886-7-5377575 • Shenzhen, China: 86-755-82514171